

**ASTERIX Part 4
Appendix A
Coding rules for
"Reserved Expansion
Field"**



Edition	:	1.1
Edition Date	:	<u>June 2005</u>
Status	:	<u>Released Issue</u>
Class	:	General Public

DOCUMENT IDENTIFICATION SHEET

DOCUMENT DESCRIPTION

Document Title

Coding rules for "Reserved Expansion Field"

EWP DELIVERABLE REFERENCE NUMBER

PROGRAMME REFERENCE INDEX

EDITION :

1.1

EDITION DATE :

June 2005

Abstract

Keywords

CONTACT PERSON : A. Engel

TEL : 93355

DIVISION : DAS/CSM

DOCUMENT STATUS AND TYPE

STATUS

Working Draft ☐
Draft ☐
Proposed Issue ☐
Released Issue ☒

CATEGORY

Executive Task ☐
Specialist Task ☐
Lower Layer Task ☒

CLASSIFICATION

General Public ☒
EATCHIP ☐
Restricted ☐

ELECTRONIC BACKUP

INTERNAL REFERENCE NAME :

HOST SYSTEM

Microsoft Windows

MEDIA

Type : Hard disk
Media Identification :

SOFTWARE(S)

DOCUMENT APPROVAL

The following table identifies all management authorities who have successively approved the present issue of this document.

AUTHORITY	NAME AND SIGNATURE	DATE
<u>ASTERIX</u> <u>Manager</u>	<u>D. Doukas</u>	
<u>SUR Domain</u> <u>Manager</u>	<u>J. Berends</u>	
<u>SURT</u> <u>Chairman</u>	<u>M. Rees</u>	
<u>EATM/DAS</u> <u>Director</u>	<u>B. Redeborn</u>	

DOCUMENT CHANGE RECORD

The following table records the complete history of the successive editions of the present document.

EDITION	DATE	REASON FOR CHANGE	SECTIONS PAGES AFFECTED
1.0	January 2003	Creation	All
0.11	March 2003	Modification of the release numbering Modification of the size of the "length field" Correction of item MD5	
<u>1.1</u>	<u>June 2005</u>	<u>Status of document: "Released Issue"</u> <u>Document ID Sheet Updated</u> <u>Document Approval Sheet updated</u> <u>Editorial "Cleanup"</u>	<u>ii</u> <u>iii</u> <u>All</u>

TABLE OF CONTENTS

DOCUMENT IDENTIFICATION SHEET	ii
DOCUMENT APPROVAL	iii
DOCUMENT CHANGE RECORD	iv
TABLE OF CONTENTS	v
EXECUTIVE SUMMARY	1
1. INTRODUCTION	2
1.1 Scope	2
2. DESCRIPTION OF THE CONTENT OF RESERVED EXPANSION FIELD	3
2.1 Length Indicator	3
2.2 Items indicator	3
2.3 MD5	4

EXECUTIVE SUMMARY

1. INTRODUCTION

1.1 Scope

This document describes the way to encode information in the Reserved Expansion Field of Monoradar Target Report from ASTERIX Cat 048.

2. DESCRIPTION OF THE CONTENT OF RESERVED EXPANSION FIELD

2.1 Length Indicator

Definition : This field indicates the total length in octets of the Reserved Expansion Field (including the REF length itself)

Format : One-octet fixed length Data Item

Structure:

Octet no. 1							
8	7	6	5	4	3	2	1
LEN							

bits 8-1

(LEN)

Length of REF in octets, including the Length Indicator itself.

Encoding Rule :

This item shall be present in every REF

2.2 Items indicator

Definition : This field indicates what are the items encoded in the REF

Format : One-octet fixed length Data Item

Structure:

Octet no. 1							
8	7	6	5	4	3	2	1
MD5	0	0	0	0	0	0	0

bits 8

(MD5)

= 0 Mode 5 Data/Reports, Extended Mode 1 Code and X Pulse are not present in the REF

= 1 Mode 5 Data/Reports and Extended Mode 1 Code and X Pulse are present in the REF

bits 7/1

Spare bits set to 0

Encoding Rule :

This item shall be present in every REF

2.3 MD5

Definition: Mode 5 Data/Reports, Extended Mode 1 Code and X pulse

Format: Compound data item comprising one primary subfield of one octet, followed by up to 7 subfields

Structure of Primary Subfield of Compound Data Item:

Octet no. 1							
8	7	6	5	4	3	2	1
SUM	PMN	POS	GA	EM1	TOS	XP	FX

bit-8, octet 1 (SUM) Subfield #1: Mode 5 Summary
 =0 Absence of Subfield #1
 =1 Presence of Subfield #1

bit-7, octet 1 (PMN) Subfield #2: Mode 5 PIN/ National Origin/Mission Code
 =0 Absence of Subfield #2
 =1 Presence of Subfield #2

bit-6, octet 1 (POS) Subfield #3: Mode 5 Reported Position
 =0 Absence of Subfield #3
 =1 Presence of Subfield #3

bit-5, octet 1 (GA) Subfield #4: Mode 5 GNSS-derived Altitude
 =0 Absence of Subfield #4
 =1 Presence of Subfield #4

bit-4, octet 1 (EM1) Subfield #5: Extended Mode 1 Code in Octal Representation
 =0 Absence of Subfield #5
 =1 Presence of Subfield #5

bit-3, octet 1 (TOS) Subfield #6: Time Offset for POS and GA.
 =0 Absence of Subfield #6
 =1 Presence of Subfield #6

bit-2, octet 1 (XP) Subfield #7: X Pulse Presence
 =0 Absence of Subfield #7
 =1 Presence of Subfield #7

bit-1, octet 1 (FX) = 0 End of Primary Subfield
= 1 Extension of Primary Subfield into next octet

**Structure of Subfield #1:
Mode 5 Summary:**

Octet no. 1							
8	7	6	5	4	3	2	1
M5	ID	DA	M1	M2	M3	MC	0

bit-8	(M5)	= 0 No Mode 5 interrogation = 1 Mode 5 interrogation
bit-7	(ID)	= 0 No authenticated Mode 5 ID reply = 1 Authenticated Mode 5 ID reply
bit-6	(DA)	= 0 No authenticated Mode 5 Data reply or Report = 1 Authenticated Mode 5 Data reply or Report (i.e any valid Mode 5 reply type other than ID)
bit-5	(M1)	= 0 Mode 1 code not present or not from Mode 5 reply = 1 Mode 1 code from Mode 5 reply.
bit-4	(M2)	= 0 Mode 2 code not present or not from Mode 5 reply = 1 Mode 2 code from Mode 5 reply.
bit-3	(M3)	= 0 Mode 3 code not present or not from Mode 5 reply = 1 Mode 3 code from Mode 5 reply.
bit-2	(MC)	= 0 Mode C altitude not present or not from Mode 5 reply = 1 Mode C altitude from Mode 5 reply
bit-1	Spare bit set to 0	

Notes:

1. The flags M2, M3, MC refer to the contents of data items I048/050, I048/070 and I048/090 respectively. The flag M1 refers to the contents of data item I048/055, Mode 1 Code in Octal Representation, and to the contents of the Subfield #5 (Extended Mode 1 Code in Octal Representation).
2. If an authenticated Mode 5 reply is received with the Emergency bit set, then the Military Emergency bit (ME) in Data Item I048/020, Target Report Descriptor, shall be set.
3. If an authenticated Mode 5 reply is received with the Identification of Position bit set, then the Special Position Identification bit (SPI) in Data Item I048/020, Target Report Descriptor, shall be set.

Structure of Subfield #2:**Mode 5 PIN /National Origin/ Mission Code**

Octet no. 1								Octet no. 2							
32	31	30	29	28	27	26	25	24	23	22	21	20	19	18	17
0	0	PIN (LSB)													

Octet no. 3								Octet no. 4							
16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1
0	0	0	NAT (LSB)					0	0	MIS (LSB)					

bits-32/31 (spare) spare bits set to 0

bits-30/17 (PIN) PIN Code

bits-16/14 (spare) spare bits set to 0

bits-13/9 (NAT) National Origin

bits-8/7 (spare) spare bits set to 0

bits-6/1 (MIS) Mission Code

Structure of Subfield #3: Mode 5 Reported Position

Octet no. 1								Octet no. 2							
48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33
Latitude in WGS 84															
Octet no. 3								Octet no. 4							
32	31	30	29	28	27	26	25	24	23	22	21	20	19	18	17
(LSB)								Longitude in WGS 84							
Octet no. 5								Octet no. 6							
16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1
(LSB)															

bits-48/25 (LAT) Latitude in WGS 84

bits-24/1 (LON) Longitude in WGS 84

Notes : Latitude in WGS 84 is expressed as a 24-bit two's complement number.
Range $-90^{\circ} \leq \text{latitude} \leq 90^{\circ}$. Sign convention: North is positive.

LSB = $180/2^{23}$ degrees = $2.145767 \cdot 10^{-05}$ degrees

Longitude in WGS 84 is expressed as a 24-bit two's complement number.
Range $-180^{\circ} \leq \text{longitude} < 180^{\circ}$. Sign convention: East is positive.

LSB = $180/2^{23}$ degrees = $2.145767 \cdot 10^{-05}$ degrees

The resolution implied by the LSB is better than the resolution with which Mode 5 position reports are transmitted from aircraft transponders using currently defined formats.

**Structure of Subfield #4:
Mode 5 GNSS-derived Altitude**

Octet no. 1								Octet no. 2							
16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1
0	RES	GA (LSB)													

bit-16 (spare) spare bit set to 0

bit-15 (RES) Resolution with which the GNSS-derived Altitude (GA) is reported.
=0 GA reported in 100 ft increments,
=1 GA reported in 25 ft increments.

bits-14/1 (GA) GNSS-derived Altitude of target, expressed as height above WGS 84 ellipsoid. GA is coded as a 14-bit two's complement binary number with an LSB of 25 ft. irrespective of the setting of RES. The minimum value of GA that can be reported is -1000 ft.

**Structure of Subfield #5:
Extended Mode 1 Code in Octal Representation**

Octet 1								Octet 2							
16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1
0	0	0	0	Extended Mode 1 Code											
				A4	A2	A1	B4	B2	B1	C4	C2	C1	D4	D2	D1

bit 16/13 Spare bits set to 0

bits-12/1 (EM1) Extended Mode 1 Code in octal representation

Note: If Subfield #1 is present, the M1 bit in Subfield #1 indicates whether the Extended Mode 1 Code is from a Mode 5 reply or a Mode 1 reply. If Subfield #1 is not present, the Extended Mode 1 Code is from a Mode 1 reply.

**Structure of Subfield #6 of Compound Data Item:
Time Offset for POS and GA**

Octet no. 1							
8	7	6	5	4	3	2	1
TOS (LSB)							

bits-8/1 (TOS)

Time Offset coded as a two's complement number with an LSB of 1/128 s. The time at which the Mode 5 Reported Position (Subfield #3) and Mode 5 GNSS-derived Altitude (Subfield #4) are valid is given by Time of Day (I048/140) plus Time Offset.

Note:

TOS shall be assumed to be zero if Subfield #6 is not present.

**Structure of Subfield #7 of Compound Data Item:
X Pulse Presence**

Octet no. 1							
8	7	6	5	4	3	2	1
0	0	0	X5	XC	X3	X2	X1

bits-8/6 spare bits set to zero

bit-5 (X5)

X-pulse from Mode 5 Data reply or Report.

= 0 X-pulse set to zero or no authenticated Data reply or Report received.

= 1 X-pulse set to one (present).

bit-4 (XC)

X-pulse from Mode C reply

= 0 X-pulse set to zero or no Mode C reply

= 1 X-pulse set to one (present)

bit-3	(X3)	X-pulse from Mode 3/A reply = 0 X-pulse set to zero or no Mode 3/A reply = 1 X-pulse set to one (present)
bit-2	(X2)	X-pulse from Mode 2 reply = 0 X-pulse set to zero or no Mode 2 reply = 1 X-pulse set to one (present)
bit-1	(X1)	X-pulse from Mode 1 reply = 0 X-pulse set to zero or no Mode 1 reply = 1 X-pulse set to one (present)

Encoding Rule:

The Reserved Expansion Field is optional. When used to transmit MD5, it shall be sent when at least one of the following conditions is satisfied:

1. The target represented by the Monoradar Target Report has been interrogated in Mode 5.
2. A non-zero Extended Mode 1 Code is received.
3. An X-pulse is present.

If condition 1 is satisfied, then Subfield #1 (Mode 5 Summary) shall be present.

If condition 2 is satisfied then Subfield #5 (Extended Mode 1 Code in Octal Representation) shall be present.

If condition 3 is satisfied, then Subfield #7 (X Pulse Presence) shall be present.