

**ASTERIX Part 4  
Appendix A  
Coding rules for  
"Reserved Expansion  
Field"**



<b>Edition</b>	<b>:</b>	<b>0.11</b>
<b>Edition Date</b>	<b>:</b>	<b>March 2003</b>
<b>Status</b>	<b>:</b>	<b>Working Draft</b>
<b>Class</b>	<b>:</b>	<b>General Public</b>

# DOCUMENT IDENTIFICATION SHEET

## DOCUMENT DESCRIPTION

### Document Title

Coding rules for "Reserved Expansion Field"

EWP DELIVERABLE REFERENCE NUMBER

PROGRAMME REFERENCE INDEX

EDITION : 0.11

EDITION DATE : March 2003

### Abstract

### Keywords

CONTACT PERSON : C. Leclerc

TEL : 93355

DIVISION : DIS/COM

## DOCUMENT STATUS AND TYPE

STATUS		CATEGORY		CLASSIFICATION	
Working Draft	<input checked="" type="checkbox"/>	Executive Task	<input checked="" type="checkbox"/>	General Public	<input checked="" type="checkbox"/>
Draft	<input type="checkbox"/>	Specialist Task	<input type="checkbox"/>	EATCHIP	<input type="checkbox"/>
Proposed Issue	<input type="checkbox"/>	Lower Layer Task	<input type="checkbox"/>	Restricted	<input type="checkbox"/>
Released Issue	<input type="checkbox"/>				

## ELECTRONIC BACKUP

INTERNAL REFERENCE NAME :

HOST SYSTEM	MEDIA	SOFTWARE(S)
Microsoft Windows	Type : Hard disk	
	Media Identification :	

## DOCUMENT APPROVAL

The following table identifies all management authorities who have successively approved the present issue of this document.

AUTHORITY	NAME AND SIGNATURE	DATE

**DOCUMENT CHANGE RECORD**

The following table records the complete history of the successive editions of the present document.

<b>EDITION</b>	<b>DATE</b>	<b>REASON FOR CHANGE</b>	<b>SECTIONS PAGES AFFECTED</b>
1.0	January 2003	Creation	All
0.11	March 2003	Modification of the release numbering Modification of the size of the "length field" Correction of item MD5	

## TABLE OF CONTENTS

<b>DOCUMENT IDENTIFICATION SHEET .....</b>	<b>ii</b>
<b>DOCUMENT APPROVAL.....</b>	<b>iii</b>
<b>DOCUMENT CHANGE RECORD .....</b>	<b>iv</b>
<b>TABLE OF CONTENTS.....</b>	<b>v</b>
<b>EXECUTIVE SUMMARY .....</b>	<b>1</b>
 <b>1. INTRODUCTION</b>	 <b>2</b>
1.1 Scope	2
 <b>2. DESCRIPTION OF THE CONTENT OF RESERVED EXPANSION FIELD</b>	 <b>3</b>
2.1 Length Indicator	3
2.2 Items indicator	3
2.3 MD5	4



## **EXECUTIVE SUMMARY**

## **1. INTRODUCTION**

### **1.1 Scope**

This document describes the way to encode information in the Reserved Expansion Field of Monoradar Target Report from ASTERIX Cat 048.




## 2. DESCRIPTION OF THE CONTENT OF RESERVED EXPANSION FIELD

### 2.1 Length Indicator

**Definition :** this field indicates the total length in octets of the Reserved Expansion Field (including the REF length itself)

**Format :** One-octet fixed length Data Item

**Structure:**



bits 8-1

(LEN)

Length of REF in octets,  
including the Length Indicator  
itself.

**Encoding Rule :**


This item shall be present in every REF

### 2.2 Items indicator

**Definition :** this field indicates what are the items encoded in the REF

**Format :** One-octet fixed length Data Item

**Structure:**



bits 8

(MD5)

= 0 Mode 5 Data/Reports,  
Extended Mode 1 Code and  
X Pulse is not present in the  
REF

= 1 Mode 5 Data/Reports and  
Extended Mode 1 Code and  
X Pulse is present in the  
REF

bits 7/1

Spare bits set to 0

**Encoding Rule :**

This item shall be present in every REF

**2.3****MD5**

**Definition:** Mode 5 Data/Reports, Extended Mode 1 Code and X pulse

**Format:** Compound data item comprising one primary subfield of one octet, followed by up to 7 subfields

**Structure of Primary Subfield of Compound Data Item:**

Octet no. 1

8	7	6	5	4	3	2	1
SUM	PMN	POS	GA	EM1	TOS	XP	FX

bit-8, octet 1 (SUM) Subfield #1: Mode 5 Summary  
=0 Absence of Subfield #1  
=1 Presence of Subfield #1

bit-7, octet 1 (PMN) Subfield #2: Mode 5 PIN/  
National Origin/Mission Code  
=0 Absence of Subfield #2  
=1 Presence of Subfield #2

bit-6, octet 1 (POS) Subfield #3: Mode 5 Reported  
Position  
=0 Absence of Subfield #3  
=1 Presence of Subfield #3

bit-5, octet 1 (GA) Subfield #4: Mode 5 GNSS-  
derived Altitude  
=0 Absence of Subfield #4  
=1 Presence of Subfield #4

bit-4, octet 1 (EM1) Subfield #5: Extended Mode 1  
Code in Octal Representation  
=0 Absence of Subfield #5  
=1 Presence of Subfield #5

bit-3, octet 1 (TOS) Subfield #6: Time Offset for POS  
and GA.  
=0 Absence of Subfield #6

=1 Presence of Subfield #6

bit-2, octet 1 (XP) Subfield #7: X Pulse Presence  
=0 Absence of Subfield #7  
=1 Presence of Subfield #7

bit-1, octet 1 (FX) = 0 End of Primary Subfield  
= 1 Extension of Primary  
Subfield into next octet

**Structure of Subfield #1:  
Mode 5 Summary:**

Octet no. 1							
8	7	6	5	4	3	2	1
M5	ID	DA	M1	M2	M3	MC	0

bit-8 (M5) = 0 No Mode 5 interrogation  
= 1 Mode 5 interrogation

bit-7 (ID) = 0 No authenticated Mode 5 ID  
reply  
= 1 Authenticated Mode 5 ID reply

bit-6 (DA) = 0 No authenticated Mode 5 Data  
reply or Report  
= 1 Authenticated Mode 5 Data  
reply or Report (i.e any valid  
Mode 5 reply type other than  
ID)

bit-5 (M1) = 0 Mode 1 code not present or not  
from Mode 5 reply  
= 1 Mode 1 code from Mode 5 reply.

bit-4 (M2) = 0 Mode 2 code not present or not  
from Mode 5 reply  
= 1 Mode 2 code from Mode 5 reply.

bit-3	(M3)	= 0 Mode 3 code not present or not from Mode 5 reply = 1 Mode 3 code from Mode 5 reply.
bit-2	(MC)	= 0 Mode C altitude not present or not from Mode 5 reply = 1 Mode C altitude from Mode 5 reply
bit-1	Spare bit set to 0	

**Notes:**

1. The flags M2, M3, MC refer to the contents of data items I048/050, I048/070 and I048/090 respectively. The flag M1 refers to the contents of data item I048/055, Mode 1 Code in Octal Representation, and to the contents of the Subfield #5 (Extended Mode 1 Code in Octal Representation).
2. If an authenticated Mode 5 reply is received with the Emergency bit set, then the Military Emergency bit (ME) in Data Item I048/020, Target Report Descriptor, shall be set.
3. If an authenticated Mode 5 reply is received with the Identification of Position bit set, then the Special Position Identification bit (SPI) in Data Item I048/020, Target Report Descriptor, shall be set.

**Structure of Subfield #2:**  
**Mode 5 PIN /National Origin/ Mission Code**

Octet no. 1								Octet no. 2							
32	31	30	29	28	27	26	25	24	23	22	21	20	19	18	17
0	0	PIN (LSB)													

Octet no. 3								Octet no. 4							
16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1
0	0	0	NAT (LSB)					0	0	MIS (LSB)					

bits-32/31 (spare)      spare bits set to 0

bits-30/17 (PIN)      PIN Code

bits-16/14 (spare) spare bits set to 0

bits-13/9 (NAT) National Origin

bits-8/7 (spare) spare bits set to 0

bits-6/1 (MIS) Mission Code

**Structure of Subfield #3:  
Mode 5 Reported Position**

Octet no. 1								Octet no. 2							
48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33
Latitude in WGS 84															

Octet no. 3								Octet no. 4							
32	31	30	29	28	27	26	25	24	23	22	21	20	19	18	17
(LSB)								Longitude in WGS 84							

Octet no. 5								Octet no. 6							
16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1
(LSB)															

bits-48/25 (LAT) Latitude in WGS 84

bits-24/1 (LON) Longitude in WGS 84

**Notes :** Latitude in WGS 84 is expressed as a 24-bit two's complement number.  
Range  $-90^{\circ} \leq \text{latitude} \leq 90^{\circ}$ . Sign convention: North is positive.

LSB =  $180/2^{23}$  degrees =  $2.145767 \cdot 10^{-05}$  degrees

Longitude in WGS 84 is expressed as a 24-bit two's complement number.  
Range  $-180^{\circ} \leq \text{longitude} < 180^{\circ}$ . Sign convention: East is positive.

$$\text{LSB} = 180/2^{23} \text{ degrees} = 2.145767 \cdot 10^{-05} \text{ degrees}$$

The resolution implied by the LSB is better than the resolution with which Mode 5 position reports are transmitted from aircraft transponders using currently defined formats.

#### Structure of Subfield #4: Mode 5 GNSS-derived Altitude

Octet no. 1								Octet no. 2							
16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1
0	RES	GA (LSB)													

bit-16 (spare) spare bit set to 0

bit-15 (RES) Resolution with which the GNSS-derived Altitude (GA) is reported.

=0 GA reported in 100 ft

increments,

=1 GA reported in 25 ft increments.

bits-14/1 (GA) GNSS-derived Altitude of target, expressed as height above WGS 84 ellipsoid. GA is coded as a 14-bit two's complement binary number with an LSB of 25 ft. irrespective of the setting of RES. The minimum value of GA that can be reported is -1000 ft.

#### Structure of Subfield #5: Extended Mode 1 Code in Octal Representation

Octet 1								Octet 2							
16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1
0	0	0	0	Extended Mode 1 Code											
				A4	A2	A1	B4	B2	B1	C4	C2	C1	D4	D2	D1

bit 16/13 Spare bits set to 0

bits-12/1 (EM1) Extended Mode 1 Code in octal representation

**Note:** If Subfield #1 is present, the M1 bit in Subfield #1 indicates whether the Extended Mode 1 Code is from a Mode 5 reply or a Mode 1 reply. If Subfield #1 is not present, the Extended Mode 1 Code is from a Mode 1 reply.

**Structure of Subfield #6 of Compound Data Item:  
Time Offset for POS and GA**

Octet no. 1							
8	7	6	5	4	3	2	1
TOS (LSB)							

bits-8/1 (TOS) Time Offset coded as a twos complement number with an LSB of 1/128 s. The time at which the Mode 5 Reported Position (Subfield #3) and Mode 5 GNSS-derived Altitude (Subfield #4) are valid is given by Time of Day (I048/140) plus Time Offset.

**Note:**  
TOS shall be assumed to be zero if Subfield #6 is not present.

**Structure of Subfield #7 of Compound Data Item:  
X Pulse Presence**

Octet no. 1							
8	7	6	5	4	3	2	1
0	0	0	X5	XC	X3	X2	X1

bits-8/6 spare bits set to zero

bit-5	(X5)	<p>X-pulse from Mode 5 Data reply or Report.</p> <p>= 0 X-pulse set to zero or no authenticated Data reply or Report received.</p> <p>= 1 X-pulse set to one (present).</p>
bit-4	(XC)	<p>X-pulse from Mode C reply</p> <p>= 0 X-pulse set to zero or no Mode C reply</p> <p>= 1 X-pulse set to one (present)</p>
bit-3	(X3)	<p>X-pulse from Mode 3/A reply</p> <p>= 0 X-pulse set to zero or no Mode 3/A reply</p> <p>= 1 X-pulse set to one (present)</p>
bit-2	(X2)	<p>X-pulse from Mode 2 reply</p> <p>= 0 X-pulse set to zero or no Mode 2 reply</p> <p>= 1 X-pulse set to one (present)</p>
bit-1	(X1)	<p>X-pulse from Mode 1 reply</p> <p>= 0 X-pulse set to zero or no Mode 1 reply</p> <p>= 1 X-pulse set to one (present)</p>

**Encoding Rule:**

The Reserved Expansion Field is optional. When used to transmit MD5, it shall be sent when at least one of the following conditions is satisfied:

1. The target represented by the Monoradar Target Report has been interrogated in Mode 5.
2. A non-zero Extended Mode 1 Code is received.
3. An X-pulse is present.

If condition 1 is satisfied, then Subfield #1 (Mode 5 Summary) shall be present.

If condition 2 is satisfied then Subfield #5 (Extended Mode 1 Code in Octal Representation) shall be present.

If condition 3 is satisfied, then Subfield #7 (X Pulse Presence) shall be present.